

HX-T4/T5/T5-BLE/T5-WIFI

RF 2.4GHz CCT controller for led dual white strips

HX-T4/T5/T5-BLE is a low-voltage controller that uses advanced PWM control technology to control various dual white temperature constant-voltage LED lamps, such as: CCT LED strips, line lights, panel lights, etc., The LEDs can be dimmed or toned according to the needs of the application to make the environment more harmonious; this product adopts 2.4G wireless remote control and excellent synchronization technology, which can realize the wireless synchronization of all controllers.



T4 (linked to RC)



T5 (unlinked to RC)



T5-BLE (TUYA Bluetooth Mesh Control)



T5-WIFI (TUYA WIFI Control)

This product supports both manual knob dimming and remote control dimming.

T4: can be controlled by any compatible remote control as default; if unique-control is needed, please matching the code before installation and using.

T5: cannot be controlled by remote control, please pair it to the remote control when remote control is required.

T5-BLE: Integrate TUYA Bluetooth mesh function based on T5, also can be controlled by remote control after pairing.

T5-WIFI: Integrate TUYA WIFI function based on T5, also can be controlled by remote control after pairing.

Please refer to the corresponding remote-control manual for operation instruction in details.


Product Feature

1. It is a constant voltage controller for CCT LEDs, working voltage is DC12-24V;
2. With power-off memory storage function;
3. The PWM frequency is adjustable, 500Hz-15.6KHz, the factory default is 2KHz;
4. With high power watt output, the maximum current is 17A/CH, 12V200W/24V400W;
5. Adopt 2.4G wireless synchronous remote control, long distance, penetrability, good synchronization, which can realize synchronous control of countless controllers; the external antenna on the receiver can be extended out of the metal shell if needed;
6. Support knob dimming, the digital tube can display the brightness percentage, and can accurately select the desired brightness or color temperature;
7. The T4 version can be controlled by the remote control by default, and the T5 version cannot be controlled by the remote control by default, which is more convenient to adapt to the needs of different scenarios;
8. T5-BLE Bluetooth controlled by Tuya Application to achieve smart control like group control, scene control, timer control and so on.
9. With short circuit protection function;
10. 3-year warranty.

Technical Parameters

Working temperature	-20-60°C	Supply voltage	DC12-24V
Output	2 channels	Static power consumption	<1W
Max. output current	17A*2CHs	Short circuit protection	Yes
Net weight	70g	External dimension	L103*W40*H24 mm
Gross weight	80g	Packing size	L110*W42*H28mm
Brightness range	0-100%	CCT range	100%WW-100%CW
RF frequency	2.4GHz	Control method	Knob, remote control, TUYA-APP
Memory function	Yes	PWM frequency	2KHz (factory default),500Hz,1KHz, 4KHz, 7.8KHz, 15.6KHz
Max. output current	PWM<=2KHz: 17A PWM=4/7.8KHz: 13A PWM=15.6KHz: 10A	Max. output power	PWM<=2KHz:200W/12V; 400W/24V PWM=4/7.8KHz:150W/12V; 300W/24V PWM=15.6KH:120W/12V; 240W/24V

Connection port instruction



Direction for use

- Connect the load wire at first, followed by the power wire; Please ensure short circuit can not occur between connecting wire before turning on the power;
- The built-in button knob of the dimmer can realize the functions of dimming and color temperature, and the two functions can be switched by short pressing the knob button;
 - 1) When dimming, the digital tube brightness display: d**, from d000 to d100, means 0%-100%;
 - 2) When adjusting the color temperature, the color temperature display of the digital tube: C**, total 100 levels, from C000 to C100, means 100%WW-100%CW;
- The PWM frequency can be adjusted through the remote control or the knob button, and the digital tube PWM display: P**, there are 6 frequencies (the maximum load current value will also be relatively adjusted), as shown below:

PWM frequency	Digital display	Max. output current/watt	
500Hz	P005	17A 200W/12V	17A 400W/24V
1KHz	P010	17A 200W/12V	17A 400W/24V
2KHz	P020	17A 200W/12V	17A 400W/24V
4KHz	P040	13A 150W/12V	13A 300W/24V
7.8KHz	P078	13A 150W/12V	13A 300W/24V
15.6KHz	P156	10A 120W/12V	10A 240W/24V

Tips: The factory default of PWM frequency is 2KHz.

PWM Frequency Adjustment operation:


1) by HX-RFBT-2.4G remote control: Press and hold the remote control “Set” for 5 seconds after switch off the dimmer by remote control(the dimmer is in off state) within10 seconds, display will show as: P**. Means enter “PWM adjusting” state. Pressing ◀/▶ to adjust the PWM frequency, pressing “Set” button again to save it after finish the setting operation. Then the dimmer return to power on state automatically.

2) by HX-RFBT10-2.4G remote control: Press and hold the remote control “Set” for 5 seconds after switch off the dimmer by remote control(the dimmer is in off state) within10 seconds, display will show as: P**. Means

enter “PWM adjusting” state. Press Brightness +/- keys to adjust the PWM frequency, pressing “Set” button again to save it after finish the setting operation. Then the dimmer return to power on state automatically.

3) by HX-RFBT12-2.4G remote control: Pressing DIY1->DIY2-> DIY1->DIY2-> DIY1->DIY2 (3 times for each) within 5 seconds after switching off the dimmer by remote control, display will show as: P***. Means enter “PWM adjusting” state.; press \wedge / \vee to adjust the PWM, pressing “DIY1” button again to save it after finish the setting operation. Then the dimmer return to power on state automatically.

4) by HX-RFBT15-2.4G remote control: Pressing C->D->C->D->C->D (3 times for each, C-matching key, D-clearing key) within 5 seconds after switching off the dimmer by remote control, display will show as: P***. Means enter “PWM adjusting” state. Rotating the knob to adjust the PWM frequency, pressing “C” button again to save it after finish the setting operation. Then the dimmer return to power on state automatically.



5) by Knob button on controller: long press the knob button for 5 seconds to enter PWM adjustment, the digital tube of the dimmer will display P***, then turn the knob to select PWM, and then short press the knob to save after selection.

Please note: PWM setting operation should be finished within 1 minute, will automatically exit PWM adjusting status without save it after 60 seconds.

Bluetooth Control Direction of Use for T5-BLE, T5-WIFI

Bluetooth / WIFI controlled by Tuya Application to achieve smart control like group control, scene control, timer control and so on.

Scan QR code from controller to download Tuya application:  (Tuya) and register it to get your home account.

Reading operation instruction of App, or following the pop-up prompt message with the APP, to finish the rest connection operation.

And compatible with voice control via Amazon Alexa, Google Assistant, Yandex Alice and so on.


Bluetooth connection reset:

Power-on and power-off 5 times (power off within 10s each time), the Bluetooth module will be reset, the load light will flash quickly, and enters the state of connection.

Tips: If the driver is not reconnected after resetting, it will automatically connect to the last device when it is powered off and on again.










Wireless-synchronization function

Receivers will transmit the control signals from the remote control and self-inspection the work statuses for each other, so multiple receivers in same zone will wireless-sync-work completely.




- Receiver (10m)
- ★ RF remote control (20m)
- RF signal repeater (30m)

Compatible remote control

Item : HX-RFBT-2.4G (1 zone)	Item : HX-RFBT10-2.4G (4 zone)	Item : HX-RFBT12-2.4G (1 zone)
		
Item: HX-RFBT15 (1 zone)	Item: HX-RFBT02B (1 zone)	Item: HX-HWP86-CCT-4S (4 zone)
		
Item: HX-HWP86-XSP (4 zone)	Item: HX-WP86-AP (RF signal repeater)	Item: HX-HWP86-CCT-2.4G (1 zone)
		

Typical Applications

Application Circuit:



Precautions

- 1.The working voltage is DC12V~24V, and it must not be connected to other voltages;
- 2.Ensure that the wiring is correct and no short circuit before power-on;
- 3.It supports wireless-sync-dimming by remote control, please refer to the remote control setting manual for details;
- 4.PWM dimming frequency is adjustable. The maximum output load power corresponding to different PWM frequencies is different. Please do not overload it.
- 5.Warranty of this product is 3 years, exclude the artificial situation of damaged or overload working.

Product information for placing order

Product name	Item number
RF 2.4GHz CCT controller for led dual white strips	T4: can be controlled by remote control as default T5: cannot be controlled by remote control T5-BLE: (with TUYA-BLE mesh function based on T5) T5-WIFI: (with TUYA WIFI function based on T5)